

ADESSO

WT-446

Professional
PMR446 Transceiver



License Free Business Radio

MAIN FEATURES

16 channels
Output power: 0.5W
Encrypted programming software
ANI and PTT-ID
Side key assignment
Busy channel lock
DTMF
0-9 grades squelch level setting

ADESSO

WT-446

Professional
PMR446 Transceiver



License Free Business Radio

16 channels · Output power: 0.5W
Encrypted programming software · ANI and PTT-ID
Side key assignment · Busy channel lock · DTMF
0-9 grades squelch level setting

Your local dealer
Walkie-talkies.com
22 Soho Mills
Wooburn Green
Buckinghamshire
HP10 0PF
T: 01494 853799



SPECIFICATION

GENERAL		TRANSMIT PART	
Frequency Range	446MHz	RF Power	0.5W
Operating Temperature	-25°C~+55°C	Modulate Mode	F3E
Frequency Combination	Phase lock frequency synthesizer	Max. Freq. Deviation	≤5KHz
Frequency Stability	±2.5ppm	Remain Wave Radiation	<-60dB
Memory Channel	16 Channels	Transmitting Current	≤1000mA
Working voltage	7.4V (Li-ion Battery)	RECEIVE PART	
Antenna Impedance	50Ω	Sensitivity	<0.25μV(12dB SINAD)
Operating Mode	Simplex of co-freq. or alien freq.	Squelch Sensitivity	<0.20μV
Dimension	113mm×55mm×32mm	Audio Power output	≤1000mW
Weight	232g (Include Battery Pack)	Receiving Current	≤100mA
		Squelch Standby	20mA

Notice: Saving your presence, no additional notice will be sent if specification changes because of technology-improving.