

PRONTO EXPRESS

Nationwide Coverage

maximon
solutions

Two-Way Radio & CCTV Specialists

Pronto Express is a Push Over Cellular (POC) long range radio which combines speed and simplicity for effective and instantaneous communication Countrywide. Calling over national cellular networks means you will never miss a transmission due to terrain, weather or distance.

Now your organisations can benefit from instant, secure communications with unlimited range, whenever and wherever you need it.



- Signal Strength Prompt
- Integrated GPS
- Selective Calling
- Private/Group Calling
- Voice Prompt
- Flash-Light
- Multi-Network Operation
- Programmable Function Button
- Licence Required



01628 878066



www.maximonsolutions.com



22 Soho Mills, Wooburn Green,
Bucks, HP10 0PF

Transportation Couriers Removal & Haulage

Specifications

Type	Parameter Item	Specification
Mechanical Properties	Model No.	Pronto Express
	Dimensions	38 (h) x 60 (w) x 135 (l)
	Weight	282g
	Working Temperature	-30°C to +75°C
Basic Parameter	Working Voltage	3.3V~4.2V (standard 3.8V)
	Working Current	500mA@LTE 300mA@WCDMA 200mA@GSM
	Peak Current	2A
RF Parameter	LTE FDD	Band 1: 2100MHz Band 3:1800MHz Band 7: 2600MHz Band 8: 900MHz Band 20: 800MHz
	WCDMA	Band 1: 2100MHz Band 8: 900MHz
	GSM	GMS/GPRS: 900/1800 MHz
	Maximum Output Power	LTE: 23 ± 2.7dBm (Power Class 3) WCDMA: 24 + 1/-3dBm (Power Class 3) GSM900: 33 ± 2dBm (Power Class 4) GSM1800: 30 ± 2dBm (Power Class 1)
	Receiving Sensitivity	LTE FDD ≤ -100dBm; WCDMA900: ≤ -108dBm; WCDMA2100: ≤ -109dBm; GSM 900/1800: ≤ -106dBm

Specifications

Type	Parameter Item	Specification
GPS	GPS	GPS Positioning, 1.57542ghZ
	Sensitivity	Catch-144dBm, Track-159dBm
Technology Standard	Data Speed Rate	LTE FDD-Uplink 50 Mbps / Downlink 150 Mbps WCDMA-Uplink 5.76 Mbps / Downlink 42 Mbps EDGE-Uplink 236.8 Kbps / Downlink 2.8 Mbps GPRS-Uplink 85.6 Kbps / Downlink 85.6 Mbps
	Protocol	Support embedded TCP&UDP Protocols; Support Protocols PAP and CHAP used for PPP connection; 3GPP TS 27.005, 27.007



Please contact Maximon Solutions for more information or to enquire about licences.

Replacement parts and additional accessories available!

Included

- Radio Body
- 5200mAh Battery
- Stubby Antenna
- Belt Clip
- Rapid Charger

 01628 878066

 www.maximonsolutions.com

 22 Soho Mills, Wooburn Green,
Bucks, HP10 0PF